

# WeTech®

## USER MANUAL

# WTC2001

Thank you for purchasing a WeTech® product. This user manual contains important safety and operating instructions for your car converter. Before using your IVA Audio Line, read this manual and all warning instructions with care in order to avoid possible danger.



Image with radio device (not included)

This product is suitable for the connecting of **DAMM FT5** radio units with **Battery FT5 Standard**.

## Safety instructions


1. Installation and the first start of the system should only be carried out by qualified technicians. When installed in a vehicle, the installation specifications of the vehicle manufacturer apply. Fasten the unit only in the interior of the vehicle.
2. The fastening material included in delivery is recommended for proper installation.
3. The use of rechargeable batteries not explicitly listed in this document may lead to fire.
4. The contacts of the product should be cleaned at regular intervals with a dry cloth. Under no circumstances should you use water or other liquids.

## Scope of delivery

The following items are included in the scope of delivery:

- 1x IVA Audio Line WTC2001
- 1x Holding bracket for WTC2001
- 1x Passive accessory set

## Start of the system



Passive accessory set


1. Connect the strands (1) of the DC cable provided to mains power. Be sure that the approved working voltage and polarity are used.
2. Mount the included holding bracket in a suitable place in the vehicle. Mounting screws for the holding bracket are not included in the scope of delivery and must be purchased separately.
3. Fasten the IVA to the holding bracket using the four knurled screws (4).
4. Insert the hollow plug (3) of the DC cable into socket (C) of the IVA.
5. Secure the connection using the cable tie (5)

**Instructions:** The DC cable includes a fuse holder (2) whose fuse will be destroyed in case of excess current. You can find information about replacement fuses in the technical data.

## Functions

The table below provides information about the function of the displays and the connections of the unit.

Pos.	Designation	Status	Description
A	Green LED	on	Battery detected.
		off	Battery not detected. Contact with the radio unit may not have been established properly.
B	Red LED	on	Quick charging active. Battery capacity under 80%
		off	Quick charging inactive. Battery capacity over 80%
C	Audio jack		Connection to speaker
D	Microphone control		Microphone sensitivity settings
E	RJ45		Socket for microphone MS62
F	DC socket		DC socket for power supply voltage in accordance with the technical data.
G	Screw		Mechanism to fix the radio in the IVA



Schematic drawing WTC2001

## Technical data

Designation	Value
-------------	-------

Working voltage	10.8V ... 31.2V
-----------------	-----------------

Output voltage	5,1 V
----------------	-------

Output current	max. 700mA
----------------	------------

Fuse	6.3 x 32 mm <sup>2</sup> / 2.5A / Inert
------	---

Degree of protection	IP20
----------------------	------

Measurements in mm	165 x 66,3 x 55,1 mm
--------------------	----------------------

Weight	326g
--------	------

## Additional instructions

### e1 type approval



The e1 type approval from the German Federal Motor Vehicle and Transport Authority confirms that this product is in compliance with the EMC regulations for motor vehicles. Devices with this type approval may therefore be mounted in vehicles without affecting the vehicle's operational permit.

### CE conformity declaration



For this product, we confirm that it meets the requirements set forth in the Directive of the Council for Conformity of Legal Regulations of Member States regarding Electromagnetic Compatibility. This declaration applies to all units manufactured in accordance with the production drawings included as a component of this declaration.

### WEEE (this symbol applies only in the European Union)



This symbol indicates that the product so labelled may not be disposed of with normal household waste. If you want to dispose of this product, obey the corresponding national laws and regulations in your country or community. The correct disposal of this product supports environmental protection and prevents possible damage to the environment and human health.

### Contact

This product was manufactured in Germany by:

WEMPE Elektronik GmbH  
Leinenweberstr. 6  
DE-36251 Bad Hersfeld

phone: +49 6621 9240-0  
fax: +49 6621 9240-44  
website: [www.wetech.de](http://www.wetech.de)  
e-mail: [info@wetech.de](mailto:info@wetech.de)